

Item	Code	Dimensions (mm)	Note
Pitch of Component	Р	12.7	Tolerance is determined by $\Delta S$ .
Pitch of Sprocket Hole	Po	12.7±0.3	
Lead Spacing	F	5.0+0.8	
Length from Hole Center to Lead	P1	3.85±0.8	
Length from Hole Center to Component Center	P <sub>2</sub>	6.35±1.3	Deviation in the feeding direction
Body Diameter	D	Please see in Ratings	
Body Thickness	Т	Please see in Ratings	
Deviation along Tape, Left or Right Defect	ΔS	±1.5	Including the inclination caused by lead bending
Carrier Tape Width	W	18.0±0.5	
Position of Sprocket Hole	W1	9.0 <sup>+0.5</sup> <sub>-0.75</sub>	Deviation of tape width
Lead Distance between Reference and	Ho	16.0±1.0	
Bottom Planes	H <sub>2</sub>	6.0 max.	
Protrusion Length	I	+0.5 to -1.0	
Diameter of Sprocket Hole	D <sub>0</sub>	4.0±0.2	
Lead Diameter	d	Please see in Ratings	
Total Tape Thickness	t1	0.6±0.3	
Total Thickness of Tape and Lead Wire	t2	2.0 max.	
Deviation across Tape	Δh1, Δh2	1.5 max.	
Portion to cut in Case of Defect	L	11.0 <sup>+0</sup> <sub>-2.0</sub>	
Hold down Tape Width	Wo	11.0 min.	
Hold down Tape Position	W2	4.0 max.	
Coating Extension on Lead	е	Up to the center of crimp	